



**TECHNICAL SPECIFICATIONS**  
**New !! Model 1523, True RMS, Wattmeter,**  
**with RS-232 Communication Interface & Special Auto-Scan function**

**2.1 Measuring Parameters :** True RMS V, A, VA, W and Frequency.

**2.2 Measuring Limits**

- a) Voltage : 75V to 130V (115V operation).
- b) Current : 0.2 to 20A RMS AC (40A peak).
- c) Volt Amperes : 1.8 to 2600VA.
- d) Power : 1 to 2600W.
- e) Power Factor : 0.5 to unity (No display).
- f) Frequency : 45 to 65Hz.

**2.3 Measurement Accuracy**

- a) Voltage / Current : 0.5% of reading ±1 digit.
- b) Volt Amperes/Power: 1% of reading ±2 digits.
- c) Power Factor : 2% of reading ±2 digits.
- d) Frequency : 0.25% of reading ±1 digit.

**Note :** i) Accuracy valid only between above specified measurement limits.  
ii) For VA, Power accuracies are valid only when voltage and current are between their respective limits.

**2.4 Measurement Resolution**

- a) Voltage : 0.1V.
- b) Current : 1mA up to 1 Amp., 10 mA above 1Amp.
- c) Volt Amperes : 1VA.
- d) Power : 1 Watt.
- e) Frequency : 0.01Hz.

**2.5 Miscellaneous**

- a) Display : 16x2 Alphanumeric LCD display.
- e) Interface : RS232.

**2.6 Power** : 75V to 130V (115V operation).

**2.7 Instrument Power Consumption** : 9W approx.

**2.8 Operating Temperature** : 5°C to 50°C, 90% RH.

**2.9 Dimensions (mm)** : 7" (W) x 8.5 (H) x 6.3" (D) approx.

**2.10 Weight** : 6lbs approx.

---