APP'D./DATE ECN# TAM 10/5/94 10882 SAFETY ORGANIZATION(S): THIS FILTER HAS BEEN FORMALLY RECOGNIZED, CERTIFIED OR APPROVED RELIABILITY SPECIFICATIONS, BY THE LISTED AGENCY. THEREFORE, ALL TEST/REQUIREMENTS SPECIFIED -40°C TO +85°C 21 DAYS @ 40°C 95% RH STORAGE TEMPERATURE: IN THE LATEST REVISION OF THE FOLLOWING AGENCY STANDARDS HUMIDITY. HAVE REEN MET. 6 TIMES RATED CURRENT FOR 8 SECONDS CURRENT OVERLOAD TEST: UL RECOGNIZED UL 1283, 544 TEST SPECIFICATIONS. CSA CERTIFIED CSA 22.2, NO.0,0.4,8 .93mH NOMINAL INDUCTANCE. VDE APPROVED VDE 565-3, 625 CAPACITANCE: (MEASURED AT 1 KHz, 0.25 VAC MAX., 25°C ±1°C) LINE TO LINE: .009µF ±20% 5 AMP., 120 VAC 4 AMP., 250 VAC OPERATING SPECIFICATIONS: DISCHARGE RESISTOR: 1.5 Mp LINE/GROUND AND LINE/LINE 6000 Ma (MIN) LINE VOLTAGE/CURRENT: 4 AMP./40°C, 250 VAC INSULATION RESISTANCE AT 100 VDC LINE FREQUENCY. 50-60Hz (W/O DISCHARGE RESISTOR) 20°C AND 50% RH MAX. LEAKAGE CURRENT, EACH 2µA AT 120V 60Hz RECOMMENDED RECEIVING INSPECTION HIPOT. LINE TO GROUND 5µA AT 250V 50Hz LINES TO GROUND: 1500 VAC FOR 1 MINUTE OPERATING AMBIENT TEMP. RANGE: -10°C TO +40°C @ RATED CURRENT, I LINE TO LINE. 1450 VDC FOR 1 MINUTE IN AN AMBIENT, Ta, HIGHER THAN 40°C, THE MAXIMUM OPERATING FILTER APPROVAL. CURRENT, I, IS AS FOLLOWS: THE BEST WAY TO SELECT AND QUALIFY A FILTER IS FOR YOUR 85-Ta ENGINEERING TO TEST THE UNIT IN YOUR EQUIPMENT. 3.32±.010 0.170 DIA 0.130R. (2 HOLES) USE ONLY WITH 0.570 1200 14 MAX. 145 DISCONNECT POWER BEFORE REPLACING FUSES 1.279 DIA. X .82° C'SINK .155±.010 DIA. 0.175 2.97±.010 (2 PLACES) -3.32±.010 -3.88 MAX. RECOMMENDED PANEL CUT-OUT NOT TO SCALE 2.92 _0.06 MAX. 1.06 MAX. 2.19 MAX. 0.39 MAX. 0.83 MAX. PROVISION FOR REMOTE POWER SWITCH MOTE! 0.28_ 1201-- 220V NOTE 2 PROVISION FOR DUAL — EUROPEAN STYLE FUSING. TRANSFORMER -240V PRIMARY TA (A) (20V NEUTRAL HILLB 100V NOTE 1. JUMPERS REQUIRED IF NO SWITCH IS USED. NOTE 2. 230V. FOR EUROPEAN APPLICATIONS. गटा ट DD 500 - 500 (MINIMUM) INSERTION LOSS FREQUENCY 2.0 . 15 .50 1.0 5.0 10 20 30 FF MHZ COMMON 19 17 G 14 18 21 22 22 19 dВ *RESISTOR ADDED TO PRODUCT BUILT AFTER 3-30-92 (9212). DIFF. UNLESS OTHERWISE SPECIFIED, TOLERANCE TO BE ±.025

MATERIAL & FINISH: AS SUPPLIED

This document is proprietary to CORCOM INC. and is not to be reproduced nor used for manufacturing purposes except on CORCOM'S prior written consent.

POWER LINE FILTER

5EHM4.05

SEHM4.05

CATALOG NO.

DATE: 4-18-94

CAD NO.

APPRVD.